

$$\varepsilon_4(\lambda) = \frac{\lambda^3}{12} \cdot \frac{B_\lambda}{C_\lambda^2 - B_\lambda D_\lambda} = \frac{\lambda^3}{12} \cdot \frac{\operatorname{sh} \lambda + \operatorname{Sin} \lambda}{1 - \operatorname{ch} \lambda \operatorname{Cos} \lambda},$$

$$\varepsilon_3(\lambda) = \frac{\lambda^3}{12} \cdot \frac{A_\lambda B_\lambda - C_\lambda D_\lambda}{C_\lambda^2 - B_\lambda D_\lambda} = \frac{\lambda^3}{12} \cdot \frac{\operatorname{sh} \lambda \operatorname{Cos} \lambda + \operatorname{ch} \lambda \operatorname{Sin} \lambda}{1 - \operatorname{ch} \lambda \operatorname{Cos} \lambda},$$

$$\varepsilon_1(\lambda) = -\frac{\lambda^2}{6} \cdot \frac{A_\lambda C_\lambda - B_\lambda^2}{C_\lambda^2 - B_\lambda D_\lambda} = \frac{\lambda^2}{6} \cdot \frac{\operatorname{Sin} \lambda \operatorname{sh} \lambda}{1 - \operatorname{ch} \lambda \operatorname{Cos} \lambda} = \mu_3(\lambda),$$

$$\varepsilon_2(\lambda) = \frac{\lambda^2}{6} \cdot \frac{C_\lambda}{C_\lambda^2 - B_\lambda D_\lambda} = \frac{\lambda^2}{6} \cdot \frac{\operatorname{ch} \lambda - \operatorname{Cos} \lambda}{1 - \operatorname{ch} \lambda \operatorname{Cos} \lambda} = \mu_4(\lambda),$$

$$\varepsilon_8(\lambda) = \frac{\lambda^3}{3} \cdot \frac{1 + \operatorname{ch} \lambda \operatorname{Cos} \lambda}{\operatorname{ch} \lambda \operatorname{Sin} \lambda - \operatorname{sh} \lambda \operatorname{Cos} \lambda}$$